



MOVEMENT SENSOR

SENSORS AND SWITCHES

Ref: 41.007

12V - 24V

A small movement sensor for inserting inside our led profiles which is activated thanks to an infrared sensor and can detect movement from a distance of approximately 2m, lighting up the led strip.

The 12V and 24V strips inside the aluminium profile can be switched ON / OFF.

Once this sensor stops detecting movement, the led strip will turn off after 40 seconds.

It is necessary to make a hole in opaque cover in the profile for the sensor to fit in.













n	()	۸1	\cap	r	

power voltage

voltage


IP20

Power (W)	120W (12V)		
Power (W)	240W (24V)		
Amps	10A		
Measurements	43x16x10mm		
Off	40 seconds		
Apt for	interior		
Waterproofing	IP20		
Packaging	1 unit		
Guarantee	2 years		
Packaging	1 unit		



Sensor mounting (orientation)







Tel: +34 916 416 081